

OPERATOR'S QUICK REFERENCE GUIDE

Function	Command	Function	Command
ADDRESS/READ CURSOR		ADDRESS/READ CURSOR	
Address cursor (column, row)	ESC = r c	Erase screen to nulls	ESC y
Address cursor (page, column, row)	ESC - p r c	Insert on	ESC q
Read cursor (row, column)	ESC ?	Edit on	ESC r
Read cursor (page, row, column)	ESC /	Page on	ESC N
INSERT CHARACTER		Line on	ESC O
Program insert character	ESC.e n	CLEAR	
TAB		Clear unprotected to insert characters	ESC + ^Z
Set typewriter (column) tab	ESC 1		ESC ;
Typewriter tab	^I	Clear all data to nulls	ESC *
Field tab	ESC i	Clear unprotected to nulls	ESC :
Back tab	ESC I	Clear page to half-intensity insert characters	ESC ,
Clear typewriter tab	ESC 2	X-ON/X-OFF	
Clear all tabs	ESC 3	Enable X-On/X-Off	^O
COMMUNICATION		Disable X-On/X-Off	^N
Local on	ESC c	DATA TERMINAL READY	
Block on	ESC B	Enable DTR	^N
Half duplex on	ESC D H	Disable DTR	^O
Full duplex on	ESC D F	SEND KEY	
Return to previous conversational mode	ESC C	Load SEND key	ESC 0 x y
EDIT KEYS		Set send delimiters	ESC x n p1 p2
Local edit keys	ESC k	Send unprotected line to cursor	ESC 4
Duplex edit keys	ESC l	Send unprotected page to cursor	ESC 5
EDITING TEXT		Send line to cursor	ESC 6
Character insert	ESC Q	Send page to cursor	ESC 7
Character delete	ESC W	Send unprotected message	ESC S
Line insert	ESC E	Send entire message	ESC s
Line delete	ESC R	Send terminal identification	ESC M
Erase line to spaces	ESC T	Send status line	ESC Z 1
Erase line to nulls	ESC t	Send user line	ESC Z 0
Erase screen to spaces	ESC Y		